

SMS Delivery – TP-STATUS (according to GSM 03.38)

Short message transaction completed

0000000 Short message received by the SME

0000001 Short message forwarded by the SC to the SME but the SC is unable to confirm delivery

0000010 Short message replaced by the SC Reserved values

0000011..0001111 Reserved

0010000..0011111 Values specific to each SC

Temporary error (or temporary status), SC still trying to transfer SM

0100000 Congestion - 32

0100001 SME busy - 33

0100010 No response from SME - 34

0100011 Service rejected - 35

0100100 Quality of service not available - 36

0100101 Error in SME - 37

0100111..0101111 Reserved

0110000.. SMS forwarded to SMSC of the operator (Axima's SMSC) - 48

0110001.. SMS was sent to Axima's SMSC (Axima's SMS Server) - 49

0110010.. SMS could not be forwarded to Axima's SMSC (Axima's SMS Server) - 50

0110011.. SMS was re-sent via another channel (Axima's SMSC) - 51

0110001..0111111 Values specific to each SC

Permanent error, SC is not making any more transfer attempts

1000000 Remote procedure error - 64

1000001 Incompatible destination - 65

1000010 Connection rejected by SME - 66

1000011 Not obtainable - 67

1000100 Quality of service not available - 68

1000101 No interworking available - 69

1000110 SM Validity Period Expired – 70

1000111 SM Deleted by originating SME - 71

1001000 SM Deleted by SC Administration - 72

1001001 SM does not exist (The SM may have previously existed in the SC but the SC no longer has knowledge of it or the SM may never have previously existed in the SC) – 73

1001010..1001111 Reserved

1010000.. Unknown subscriber - 80

1010001.. Call Barred (blocked subscriber) - 81

1010002.. Unexpected data value (bad SMS?) - 82

1010000..1011111 Values specific to each SC

11000000 Remote procedure error (Axima's SMSC)

11000001 Incompatible destination (Axima's SMSC)

Temporary error, SC is not making any more transfer attempts

1100000 Congestion - 96

1100001 SME busy - 97

1100010 No response from SME - 98

1100011 Service rejected - 99

1100100 Quality of service not available - 100

1100101 Error in SME - 101

1100110..1101001 Reserved

1101010..1101111 Reserved

1110000..1111111 Values specific to each SC

Index:

SME	Short Message Entity (mobile device)
SM	Short Message
SC	Axima's Service Centre